

Von Neumann Quantum Processors^{*}

Alexander Yu. Vlasov[†]

Federal Radiological Center (IRH)
197101 Mira Street 8, St.–Petersburg, Russia

ABSTRACT

Most modern classical processors support so-called *von Neumann architecture* with program and data registers. In present work is revisited similar approach to models of quantum processors. Deterministic programmable quantum gate arrays are considered as an example. They are also called *von Neumann quantum processors* here and use conditional quantum dynamics. Such devices have some problems with universality, but consideration of hybrid quantum processors, *i.e.*, models with both continuous and discrete quantum variables resolves the problems. It is also discussed comparison of such a model of quantum processors with more traditional approach.

1 Introduction

So-called von Neumann architecture was used already in first electronic computers like EDVAC [1] more than 50 years ago. Main idea of such approach is storage of program in computer memory, unlike of some elementary electronic calculators.

Such idea is also appropriate for quantum computers and present work recollects some previous discussions [2, 3, 4, 5]. General idea of such approach — is to consider a Hilbert space of composite quantum system with two parts:

$$\mathcal{H} = \mathcal{H}_c \otimes \mathcal{H}_d. \quad (1)$$

^{*}304th WE-Heraeus-Seminar ‘Elementary Quantum-Processors,’ 13–15 October 2003

[†]Electronic mail: Alexander.Vlasov@Pobox.spbu.ru

Here $\mathcal{H}_d$ is a Hilbert space of quantum system considered as *data*, and $\mathcal{H}_c$ is Hilbert space of “*code*”, i.e., *program*.

2 Quantum processing units

2.1 Programmable quantum gate arrays

The programmable quantum gate array [2, 6, 8, 9] or *quantum processor* [3, 10] — is a quantum circuit with fixed structure. Similarly with classical von Neumann Architecture here are *data register* $|\psi\rangle \in \mathcal{H}_d$ and *program (code) register* $|c\rangle \in \mathcal{H}_c$. Different operations $\mathbf{u}$ with data are indexed by a state of the program (code)

$$\mathbf{Q}_{\text{PU}}: (|c\rangle \otimes |\psi\rangle) \mapsto |c'\rangle \otimes (\mathbf{u}_c|\psi\rangle). \quad (2)$$

It was discussed already in [6], that Eq. (2) is compatible with unitary quantum evolution, if different states of *program register* are orthogonal — due to such requirement number of accessible programs coincides with dimension of Hilbert space and it produces some challenge for construction of universal quantum processors. It was suggested few ways around such a problem: to use specific “stochastic” design of universal quantum processor [6, 8, 9, 10], to construct (non-stochastic) quantum processor with possibility to approximate any gate with given precision [2, 3, 8, 9] (it is also traditional approach to universality [11, 12, 13], sometime called “universality in approximate sense” [14]).

2.2 Conditional quantum dynamics

In finite-dimensional case unitary operator $\mathbf{Q}_{\text{PU}}$ satisfying Eq. (2) can be simply found [2, 3]. Let us consider case with $|c'\rangle = |c\rangle$ in Eq. (2). It was already mentioned, that states $|c\rangle$ of program register corresponding to different operators $\mathbf{u}_c$ are orthogonal and, so, may be chosen as basis. In such a basis $\mathbf{u}_c$ is simply set of matrices numbered by integer index c , and operator $\mathbf{Q}_{\text{PU}}$ Eq. (2) can be written as block-diagonal $NM \times NM$ matrix:

$$\mathbf{Q}_{\text{PU}} = \begin{pmatrix} \mathbf{u}_1 & & & 0 \\ & \mathbf{u}_2 & & \\ & & \ddots & \\ 0 & & & \mathbf{u}_M \end{pmatrix}, \quad (3)$$




Figure 1: Von Neumann quantum processor with three buses.

with $N \times N$ matrices $\mathbf{u}_c$, if dimensions of program and data registers are M and N respectively;

$$\mathbf{Q}_{\text{PU}} = \sum_{c=1}^M |c\rangle\langle c| \otimes \mathbf{u}_c, \quad (4)$$

It is *conditional quantum dynamics* [7]. For quantum computations with qubits $M = 2^m$, $N = 2^n$.

2.3 Three-buses design

Operator $\mathbf{Q}_{\text{PU}}$ described above is only first approach to von Neumann quantum processors. Such *quantum processing unit* (QPU) simply generates some gate *encoded* (indexed) by state of program register. For performing arbitrary sequence of operations it is possible to use more difficult design [2, 3, 5].

Let us instead of one program (code) register $\mathcal{H}_c$ consider compound system $\mathcal{H}_p \otimes \mathcal{H}_c$, there $\mathcal{H}_p$ corresponds to “program memory” in von Neumann architecture. Then Hilbert space of such von Neumann quantum processor

may be described as

$$\mathcal{H} = \mathcal{H}_p \otimes \mathcal{H}_c \otimes \mathcal{H}_d. \quad (5)$$

Let us use simplest example with “cyclic memory” (resembling *Hg delayed-line memory* of some old classical computers). In this example $\dim \mathcal{H}_c = M$ and it is necessary to have possibility to perform any sequence of up to P operators $\mathbf{u}_c$ with data register. Then it is possible to consider $\dim \mathcal{H}_p = M^P$ (it is mP qubits for $M = 2^m$) and write basic states $|p\rangle|c\rangle \in \mathcal{H}_p \otimes \mathcal{H}_c$ as

$$|p\rangle|c\rangle \equiv |p; c\rangle \equiv |c_P, \dots, c_1; c_0\rangle, \quad (6)$$

where $c_i < M$ are integer indexes and $c_0 \equiv c$ is index in $\mathcal{H}_c$. It is possible to consider *right cyclic shift operator* S_{hft} acting on $\mathcal{H}_p \otimes \mathcal{H}_c$ as

$$S_{\text{hft}}: |c_P, c_{P-1} \dots, c_1; c_0\rangle \mapsto |c_0, c_P, \dots, c_2; c_1\rangle \quad (7)$$

Now it is possible to compose application of S_{hft} Eq. (7) operator on first two terms in Eq. (5) $\{\mathcal{H}_p \otimes \mathcal{H}_c\}$ with Q_{PU} on $\mathcal{H}_c \otimes \mathcal{H}_d$. Then it is possible to write for P applications of such compound operator $S_{\text{hft}}Q_{\text{PU}}$

$$(S_{\text{hft}}Q_{\text{PU}})^P: (|p; c\rangle|\psi\rangle) \mapsto |p; c\rangle(\mathbf{u}_{c_P} \dots \mathbf{u}_{c_1}|\psi\rangle) \quad (8)$$

and it is possible to implement any sequence with P operators using different programs $|p; c\rangle$.

It should be mentioned, that instead of cyclic shift operator it is possible to use arbitrary reversible algorithm for generation of indexes in register $|c\rangle$ and so general three-buses design may be depicted on Fig. 1. Here Hilbert spaces $\mathcal{H}_p$, $\mathcal{H}_c$ and $\mathcal{H}_d$ are called *pseudo-classical*, *intermediate* and *quantum data buses* respectively [2, 3, 5].

3 Hybrid quantum processors

Here is also revisited [5] an alternative approach for strictly universal quantum processor — to use continuous quantum variables in program register and discrete ones for data, *i.e.* *hybrid* quantum computer [16]. In such a case number of different programs is infinite and it provides possibility to construct strictly universal hybrid quantum processor for initial (“deterministic”) design described by Eq. (2). It is enough to provide procedures for one-qubit rotations with three real parameters together with some finite number of two-gates [14, 15].




Figure 2: Hybrid quantum processing unit. ($\theta_k \equiv \theta_{k,(p)} = e^{2\pi i p \sigma_k}$)

Generalization to hybrid system with program register described by one continuous quantum variable and qubit data register is straightforward. The states of program register may be described as Hilbert space of functions on line $\psi(x)$. In coordinate representation a basis is

$$|q\rangle = \delta(x - q); \quad \langle q | \psi(x) \rangle = \psi(q). \quad (9)$$

Let's represent some continuous family of gates $\mathbf{u}_{(q)}$ acting on data state, say controlled qubit rotations

$$\theta_{j,(q)} = \exp(2\pi i q \sigma_j), \quad (10)$$

where σ_j are three Pauli matrices. It is possible to write continuous analog of Eq. (4):

$$\mathbf{Q}_{\text{PU}} = \int dq (|q\rangle \langle q| \otimes \mathbf{u}_{(q)}), \quad (11)$$

$$\mathbf{Q}_{\text{PU}}(\psi(x)|s\rangle) = \int \delta(x - q) \psi(q) |\mathbf{u}_{(q)} s\rangle dq = \psi(x) |\mathbf{u}_{(x)} s\rangle, \quad (12)$$

where $\otimes$ is omitted because $|\psi\rangle|s\rangle$ can be considered as product of scalar function $\psi(x)$ on complex vector $|s\rangle$. Finally:

$$\mathbf{Q}_{\text{PU}}(|q\rangle|s\rangle) = |q\rangle|\mathbf{u}_{(q)}s\rangle. \quad (13)$$

It is convenient also to use momentum basis, *i.e.*:

$$|\tilde{p}\rangle = e^{ipx}; \quad \langle \tilde{p} | \psi(x) \rangle = \int e^{-ipx} \psi(x) dx \equiv \tilde{\psi}(p). \quad (14)$$

(where $\tilde{\psi}$ is Fourier transform of ψ) and operator $\tilde{\mathbf{Q}}_{\text{PU}}$:

$$\tilde{\mathbf{Q}}_{\text{PU}} = \int dp (|\tilde{p}\rangle \langle \tilde{p}| \otimes \mathbf{u}_{(p)}), \quad (15)$$

$$\tilde{\mathbf{Q}}_{\text{PU}}(|\tilde{p}\rangle|s\rangle) = |\tilde{p}\rangle|\mathbf{u}_{(p)}s\rangle. \quad (16)$$

It has simpler physical interpretation. Let us consider scattering of some scalar particle on quantum system with two states (qubit). Then Eq. (16) can be written symbolically as:

$$\text{~~~~~}|\exp(ikx)\rangle_1 \rightarrow \bullet \nearrow^{|s\rangle_2} \quad \Longrightarrow \quad \bullet \nwarrow^{\mathbf{u}_{(k)}|s\rangle_2} \text{~~~~~}|\exp(ikx)\rangle_1 \rightarrow$$

Using such approach with hybrid program register (few continuous variables for different qubit rotations and discrete ones for two-gates like CNOT), it is possible to suggest design of universal quantum processor with qubits data register.

Hilbert space of hybrid system with k continuous and $M = 2^m$ discrete quantum variables can be considered as space of $\mathbb{C}^M$ -valued functions with k variables

$$F(x_1, \dots, x_k): \mathbb{R}^k \rightarrow \mathbb{C}^M.$$

For construction of universal processor it is possible to use three continuous variables for each qubit together with discrete variables for control of two-qubit gates (see Fig. 2).

4 Comparison with more traditional models

On the one hand, model of von Neumann quantum processor discussed in present paper looks rather difficult for realization and author did not hear

about any proposal for experimental implementation of such model. Of course, formally even **Controlled-NOT** or more general **Controlled-U** quantum gates satisfy QPU design Eq. (2), but they are too simple gates for serious discussions.

On the other hand, it is clear, that modern situation, when for control of quantum processing are used some macroscopic and even huge equipment may be not very convenient from point of view of possible further plan to design *elementary quantum processors*.

There is yet another advantage of discussed approach. Paradigm of hybrid quantum processor discussed above formally *includes even more traditional design*, because continuous quantum variables without superposition used in such model are analogues of classical variables like different kind of electromagnetic (including light) signals used for construction of Hamiltonians for control of quantum gates almost in any approach to quantum processing.

References

- [1] A. Burks, H. Goldstine, J. v. Neumann, *Preliminary discussion of the logical design of an electronic computing instrument*, **4** (Princeton 1946).
- [2] A. Yu. Vlasov, “Classical programmability is enough for quantum circuits universality in approximate sense,” **quant-ph/0103119**, (2001).
- [3] A. Yu. Vlasov, “Universal quantum processors with arbitrary radix $n \geq 2$,” (Proc. ICQI 2001); **quant-ph/0103127**, (2001).
- [4] A. Yu. Vlasov, “ $\aleph_{QP}$: Universal hybrid quantum processors,” (Proc. QPC 2002); **quant-ph/0205074**, (2002).
- [5] A. Yu. Vlasov, “Quantum Processors and Controllers,” (Proc. PhysCon 2003); **quant-ph/0301147**, (2003).
- [6] M. A. Nielsen and I. L Chuang, “Programmable quantum gate arrays,” *Phys. Rev. Lett.* **79** 321–324, (1997).
- [7] A. Barenco, D. Deutsch, A. K. Ekert, and R. Jozsa, “Conditional quantum dynamics and logic gates,” *Phys. Rev. Lett.* **74**, 4083–4086 (1995).

- [8] G. Vidal, and J. I. Cirac, “Storage of quantum dynamics on quantum states: A quasi-perfect programmable quantum gate,” `quant-ph/0012067` (2000).
- [9] G. Vidal, L. Masanes, and J. I. Cirac, “Storing quantum dynamics in quantum states: stochastic programmable gate for $U(1)$ operations,” *Phys. Rev. A* **88**, 047905 (2002); `quant-ph/0102037` (2001).
- [10] M. Hillery, V. Buzek, and M. Ziman, “Probabilistic implementation of universal quantum processors,” *Phys. Rev. A* **65**, 022301 (2002); `quant-ph/0106088` (2001).
- [11] D. Deutsch, “Quantum Theory, the Church-Turing Principle and the Universal Quantum Computer,” *Proc. R. Soc. London Ser. A* **400**, 97–117 (1985).
- [12] D. Deutsch, “Quantum Computational Networks,” *Proc. R. Soc. London Ser. A* **425**, 73–90 (1989).
- [13] D. Deutsch, A. Barenco, and A. Ekert, “Universality in quantum computation,” *Proc. R. Soc. London Ser. A* **449**, 669–677 (1995).
- [14] R. Cleve, “An introduction to quantum complexity theory,” `quant-ph/9906111`, (1999).
- [15] A. Barenco, C. H. Bennett, R. Cleve, D. P. DiVincenzo, N. Margolus, P. W. Shor, T. Sleator, J. A. Smolin, and H. Weinfurter, “Elementary gates for quantum computation,” *Phys. Rev. A* **52**, 3457–3467 (1995); `quant-ph/9503016`.
- [16] S. Lloyd, “Hybrid quantum computing,” `quant-ph/0008057`, (2000).
- [17] S. Lloyd, and S. L. Braunstein, “Quantum computation over continuous variables,” *Phys. Rev. A* **82**, 1784–1787 (1999); `quant-ph/981082`, (1998).
- [18] M. Hillery, M. Ziman, and V. Buzek, “Implementation of quantum maps by programmable quantum processors,” *Phys. Rev. A* **66**, 022301 (2002); `quant-ph/0205050`.